


Soft plug

**BJ-2 series** (10pcs/pack)


- This plug is used for checking power supply and signal.
- Please use BQ-2, BF-2-13, BM-2-11 on the insertion side.
- Material Main body: Brass  
Spring part: Beryllium copper  
Resin part: Acetal copolymer (UL94HB)  
(Color: BLACK, RED, YELLOW, GREEN, BLUE, WHITE)
- Rated current: 10A
- Contact resistance: 10m Ω or less (Insertion side: BQ-2, BF-2-13, BM-2-11)
- Insulation resistance: 500M Ω or over
- Withstand voltage: 1000V AC, DC per minute
- Adaptive Jack: BQ-2, BF-2-13, BM-2-11
- Operating temperature range: - 40 to + 85°C



■ Example of usage



When BF-2-13 is used on the insertion side



When BM-2-11 is used on the insertion side


■ Part No.

Part No.	Finish	Electric wire pinstallation method
BJ-2-1-G	Gold plating over nickel base	Solder
BJ-2-1-N	Nickel plating	Solder
BJ-2-2-G	Gold plating over nickel base	Crimping
BJ-2-2-N	Nickel plating	Crimping

\* Please use the tool OMXT-1 for crimping.  
(Please take off the edge tool.)

■ How to order

BJ-2-1-G RED



■ Dimension

