



Wrapping terminal

WR series (1000pcs/pack)

- This terminal is for wrapping.
- Material: Phosphor bronze board thickness: t0.64
- Finish: Gold plating over nickel base
- PC board fitting hole: Common board: ϕ 0.9
Through hole board: ϕ 1.0

| Part No. | L |
|----------|----|
| WR-0 | 8 |
| WR-1 | 9 |
| WR-2 | 14 |
| WR-3 | 19 |





Wrapping terminal

WH series (1000pcs/pack)

- This terminal is for wrapping.
- As this terminal has a click, you can fix it at a certain height.
- Material: Phosphor bronze \square 0.635
- Finish: Gold plating over nickel base
- PC board fitting hole: ϕ 1.0

| Part No. | L | Press-fitting tool edge chip |
|----------|----|------------------------------|
| WH-8 | 8 | P-11 |
| WH-10 | 10 | P-12 |
| WH-14 | 14 | P-13 |





* The press-fitting tool edge chip, P series, is not operable without the main unit, PCX-1

Wrapping terminal

WK series (1000pcs/pack)

- This terminal is for wrapping.
- Material: Phosphor bronze \square 0.635
- Finish: Gold plating over nickel base
- PC board fitting hole: ϕ 1.0

| Part No. | L |
|----------|----|
| WK-11 | 11 |
| WK-13 | 13 |
| WK-17 | 17 |
| WK-21 | 21 |
| WK-27 | 27 |





Wrapping terminal

WB series (1000pcs/pack)

- This terminal is for wrapping.
- Material: Phosphor bronze \square 0.5
- Finish: Gold plating over nickel base
- PC board fitting hole: ϕ 0.8

| Part No. | L | Press-fitting tool edge chip |
|----------|----|------------------------------|
| WB-7 | 7 | P-14 |
| WB-10 | 10 | P-15 |



* The press-fitting tool edge chip, P series, is not operable without the main unit, PCX-1

Wrapping terminal

WA series (1000pcs/pack)

- This terminal is for wrapping and for putting a PC board at right angle.
- Material: Phosphor bronze \square 0.635
- Finish: Gold plating over nickel base
- PC board fitting hole: ϕ 1.0

| Part No. | L |
|----------|----|
| WA-6 | 6 |
| WA-10 | 10 |

