Spacer for surface mounting (inch type)

SSB series

- A chip mounter can be used for this spacer.
- Please fit to the surface mounting board and solder by reflow.

• This can be used for various purposes such as fitting of a panel, fitting to a housing, and supplying of electric wire.


- Please remove the adsorption film after reflow.
- The jig for removing adsorption films (Part No.: TH-JIG) is available.
- Material: Brass
- Finish: Tin plating over nickel base
- Tap: No 2-56 type P = 0.4536 No 4-40 type P = 0.6350

Part No.	А	В	L	М	Package
SSB-2.5 (2-56)	3.5	4.5	2.5	2-56	Reel (500pcs/reel)
SSB-3.0 (2-56)	3.5	4.5	3.0	2-56	Reel (500pcs/reel)
SSB-3.5 (2-56)	3.5	4.5	3.5	2-56	Reel (400pcs/reel)
SSB-4.0 (2-56)	3.5	4.5	4.0	2-56	Reel (400pcs/reel)
SSB-4.5 (2-56)	3.5	4.5	4.5	2-56	Reel (350pcs/reel)
SSB-5.0 (2-56)	3.5	4.5	5.0	2-56	Reel (350pcs/reel)
SSB-2.5 (4-40)	4.0	5.0	2.5	4-40	Reel (500pcs/reel)
SSB-3.0 (4-40)	4.0	5.0	3.0	4-40	Reel (500pcs/reel)
SSB-3.5 (4-40)	4.0	5.0	3.5	4-40	Reel (400pcs/reel)
SSB-4.0 (4-40)	4.0	5.0	4.0	4-40	Reel (400pcs/reel)
SSB-4.5 (4-40)	4.0	5.0	4.5	4-40	Reel (350pcs/reel)
SSB-5.0 (4-40)	4.0	5.0	5.0	4-40	Reel (350pcs/reel)

■ Tightening torque

SSB- \square (2-56) ······3.0kgf-cm (29.4N-cm) or less SSB- \square (4-40) ······3.0kgf-cm (29.4N-cm) or less

 We also sell the bulk product (without adsorption film).



Recommended land information




SSB- ☐ (2-56) ······ 5.0 SSB- ☐ (4-40) ······ 5.5

Recommended metal mask thickness

 $150 \mu m$ to $200 \mu m$





Example of usage



■ Instructions for use

Solder may go up to the screw part.

The section of the BC beautiful and the BC beautifu

Therefore, the screw on the PC board side may become hard by 1 to 2 threads.

- Please use it with the specified tightening torque or less.
- Making the metal mask thickness thicker is effective for increasing the torque.

